

OCBS -D7000 Android

OCBS -D7000

□□

- Android 7.0
- 2 GB RAM □ 16 GB ROM
- 4.0□.480 * 800 WVGA IPS□□
- 1D / 2D□□□□□□□□
- RFID LF / HF / UHF / for optional
- □□& Functional keyboards
- □□4G / Wifi / GPS /□□
- □□□□5 MP□□LED□□□□□□□□
- □□□□□□□□3.7V□5200 mAh□□
- □□□IP65 / 1.5 mDrop□□□

□□	
□□□□	
□□	158□□□□□x 75□□□□□x 28□□□□□±2□□
□□	□□□300□□□□□□□□□□
□□	4.0□□TFT-LCD□WVGA 480x800□□□□□□□□
□□	LED□□
□□	3□TP□□17□□□□□4□□□
□□	2□PSAM□1□SIM□1□TF
□□	□□□□□□□□3.7V□5200mAh
□□□□	
□□□□□	Cortex A7 1.2 GHz□□
□□□□	Android 7.0
□□□□	2 GB RAM□16 GB ROM□MicroSD□□□32 GB□□□
□□□□	
□□□□□	-20°C□50°C
□□□□	-20°C□70°C
□□	5□□□□□□95□RH□□□□□
□□□□	□□□□□□□□5□□/1.5□□□□□□□□
□□	IP65□IEC□□□
ESD	±15kV□□□±8kv□□□□□±8kv□□□□
□□□□	
SDK	HHW□□□□□□
□□	Java□
□□	Android Studio□Eclipse
□□□□	
WWAN	WCDMA□850/1900 / 2100MHz□□GSM / GPRS / Edge 850/900/1800 / 1900MHz□
WLAN	IEEE 802.11 b / g / n
WPAN	□□Class v2.1 + EDR□□□v3.0 + HS□□□v4.0

□□□□□□	GPS□□□□A-GPS□□□□□5□	
□□□□□		
□□□□□□□□□□		
1D□□□	□□□□□□	□□□□N431x
	□□	□□□□□□□□





OCBS-D7000





OCBS-D7000





OCBS-D7000

