

Support Windows/Java/Android/IOS 80mm Portable Printer Bluetooth (Model: OCPP-M082)

Specifications:

| | |
|------------------------|---|
| Dimensions (W × D × H) | 98 × 103 × 45mm |
| Weight | 280 g |
| Color | Black |
| Effective print width | 72 mm |
| Printing method | Thermal Line Printing |
| Print command | ESC / POS compatible instruction set |
| Print speed | To 90mm/sec |
| Resolution | 8 dots / mm (203DPI) |
| Print Font | In 12X24 / 24x24 in |
| Column capacity | 48/ 24columns |
| Character size | 1.5 × 3.0 mm (width x height) / 3.0x3.0mm (width x height) |
| Paper Size | Diameter of 80.0 mm to ± 0.1mm x30.0 |
| Paper Thickness | 0.06 to 0.08 mm |
| Character set | Alphanumeric / Chinese Text |
| Interface | USB, RS-232, Bluetooth (optional) |
| Flash | 256KB |
| Power Adapter | 9V DC/2A |
| Battery Power | DC / 2000 mA 7.4V; battery can stay in 4-5 days, when it is full of strength, it can print 120-150M Paper |
| Other Features | Paper detection, power detection, manually shut down |
| Working conditions | Temperature: -10degreeC~50degreeC Humidity: 10%~90% |
| Storage conditions | Temperature: -20degreeC~70 degreeC Humidity: 5%~95% |
| Device Name | Can be customized to select letters and numbers up to 30 ASCII characters. |
| Password | Default Input pairing code "1234" It can be customized. Maximum 6 digitals. |
| Size of the power plug | 3.5 * 1.1 mm |

| | P/N | Description |
|----------------------|-----------------|--|
| Ordering information | OCPP-M082-BB | With Bluetooth and battery,support Android |
| | OCPP-M082-BB-AI | With Bluetooth and battery,support Android and IOS |
| | OCPP-M082-UB | With Battery USB Communication, |
| | OCPP-M082-U | USB Communication,without BT,Battery |
| | OCPP-M082-B | Bluetooth Communication,without Battery |
| | OCPP-M082-UC | USB Communication,with Car Charger |
| | OCPP-M082-BC | Bluetooth Communication with Car Charger |
| | OCPP-M082-C | Other Customized |
| | | |

Product Details:



Relevant documents:

- *[Specification](#)
- *[Program Manual](#)
- *[Instruction Manual](#)
- *[Driver for WinXP Win2000 WinVista Win7 Win8-32bit](#)
- *[Driver for Win7 Win8-64bit](#)
- *[Driver for Linux](#)
- *[Printer Parameters Setting Tools](#)
- *[USB Printdemo\(Application Software demo\)](#)
- *[Bluetooth Printdemo\(Application Software demo\)](#)
- *[SDK for Android](#)
- *[CD Files](#)