

**Tastiera programmabile pos KB101 Tastiera 101 tasti con lettore di schede
(Modello numero.: KB101)**

Specificazioni:

Utilizzare i tasti film ad alta resistenza, bello da sentire;
Simboli keycap incisi a laser o simboli keycap stampati UV serigrafici di alta qualità;
La vita di Key & gt; 10 milioni di volte;
Le tastiere sono supportate da una cornice metallica spessa;
Supporta DOS, Windows9X / 2000 / ME / NT / XP;
Supporto per impostare la chiave elettronica secondo richiesta;
Interfaccia: PS / 2;
Potere di lavoro: + 5V / DC +/- 5%;
Corrente di lavoro: & lt; 300mA;
Dimensioni: 395 x 160 x 40 (mm);
Peso: 1 kg;

Osservazioni:

Può essere trasformato KB programmabile come per richiesta (20 Programmable chiavi per ciascuno E2 PROM, può salvare i dati per 100 anni senza batteria), apuò anche essere aggiunto un lettore di carte a banda magnetica.



KB101



www.ocominc.com







Contatto:

Harold Hu

OCOM Technologies Limited

Indirizzo: 4 / F, Block 10, Zhongxing Industrial Park, Chuangye Road, Distretto di Nanshan, Shenzhen 518054, Cina;

Sito Web: www.ocominc.com, www.possolution.com.cn;

E-mail: sales14@ocominc.com;

Skype: [sales14@ocominc.com](https://www.skype.com/people/sales14@ocominc.com)

MSN: ocomsales14@hotmail.com;

Whatsapp: 86.18948789890;

Wechat: 18948789890 (ocomsales14);

Cellulare: 86.18948789890;

QQ: 1467261417;

Tel: 0086.755.86053207-814;

Fax: 0086.755.86053207-868.